



## Applicable Models

- 12RES
- 14RCA
- 14RCAL
- 14RESA (120 and 240 Volts)
- 14RESAL
- 20RCA
- 20RCAL
- 20RESC (120 and 240 Volts)
- 20RESCL
- 20RESD
- 24/30RCL
- 38/48/60RCL
- 38RCLB
- 48RCLB
- 60RCLA
- 80- 100ERESD
- 125- 150ERESC
- KG80R
- KG100R
- KG125R

## Description

The battery heater kit includes a battery heating wrap to help increase the battery temperature in cold climates. The battery heater is connected to a thermostat for controlled heating. When temperatures fall below 16°C (60°F), the thermostat turns the heater on, maintaining optimum battery temperature. The thermostat turns the heater off at 27°C (80°F).

Battery heater kits are recommended for generators installed in regions where the temperature regularly falls below 0°C (32°F).

**Note:** Battery is not included with heater kit.

## Specifications

Kit Number	GM92406-KP2-QS	GM92406-KP3-QS	GM104703-KP1
Volts	240	120	120
Heater wrap rating, Watts	50		65
Battery wrap length, mm (in.)	864 (34)		1067 (42)
Power cord length, mm (in.)	1830 (72)		1677 (66)
Thermostat on temperature	16°C (60°F)		
Thermostat off temperature	27°C (80°F)		

## Kit Selection

Kit Number	Generator Set Model
GM104703-KP1	24/30RCL 38RCLB 48RCLB 60RCLA 80-100ERESD 125-150ERESC KG80R-KG125R
GM92406-KP2-QS	14RESA (240 Volts) 14RCA/RCAL (240 Volts) 20RESC (240 Volts) 20RCA/RCAL (240 Volts)
GM92406-KP3-QS	12RES 8/10/12RESV/RESVL 14RCA/RCAL (120 Volts) 14RESA/RESAL (120 Volts) 20RCA/RCAL (120 Volts) 20RESC/RESCL (120 Volts) 20RESD

**Note:** Residential/Light Commercial Model generator sets listed on this specification sheet are current at the time of publication. The battery heater kits listed above may also apply to other models that are not shown, including selected Industrial models. Refer to the Kohler Price List for kit applicability.

**DISTRIBUTED BY:**

Availability is subject to change without notice. Kohler Co. reserves the right to change the design or specifications without notice and without any obligation or liability whatsoever. Contact your local Kohler® generator set distributor for availability.

© 2013, 2014, 2015, 2016, 2018, 2019 by Kohler Co. All rights reserved.